

# LCGT Interface Control Document

System Engineer Office (SEO)

December 12, 2011

# 1 Overview

This document presents the interface information that should be shared by more than one of the 14 existing LCGT subsystems. The interface information includes (i) definition of each subsystem, (ii) interface parameter list, and (iii) optical layout of the detector. The document is uploaded on the LCGT SVN server (<https://granite.phys.s.u-tokyo.ac.jp/svn/LCGT/trunk/ICD>) and the contents are to be updated on a real-time basis.

## 2 Allocation of the tasks for LCGT

The scope of each subsystem and the boundaries of subsystems are defined so that all the LCGT components must be included in one or more subsystems. The components shared by more than one subsystems, namely *interface components*, should be carefully controlled to avoid a contradictory assumption of the setup.

### 2.1 List of the subsystems and 3-letter codes

Analog Electronics (AEL)  
Auxiliary Optics (AOS)  
Cryogenics (CRY)  
Digital System (DGS)  
Facility (FCL)  
Input and Output Optics (IOO)  
Laser (LAS)  
Main Interferometer (MIF)  
Mirror (MIR)  
Tunnel (TUN)  
Vacuum (VAC)  
Vibration Isolation System (VIS)

### 2.2 Environmental setup components

3km tunnels [TUN], Water drainage system [TUN], car parking [FCL], air conditioners [FCL], thermometers [GIF], microphones [GIF], barometers [GIF],	center room [TUN], entrance tunnel [TUN], power supply system [FCL], optical fibers [FCL], seismometers [GIF], hygrometers [GIF], accelerometers [GIF],	two-story end rooms [TUN], buildings [FCL], clean assy rooms [FCL], cranes [FCL], particle meters [GIF], baseline interferometers [GIF],
---	---	---

### 2.3 Vacuum/cryostat components

chambers (A,B,C1,C2) [VAC], borehole tubes [VAC], baffles for radiation [VAC], vacuum gauges [VAC], radiation shields (8K, 80K) [CRY], compressor [CRY], vibration reduction system [CRY], heat conductors [CRY], vacuum access [FCL],	beam tubes [VAC], bellows [VAC], viewports [VAC], vacuum pumps (turbo, ion) [VAC], radiation shield supports [CRY], valve unit [CRY], 1st cold stage [CRY], vacuum chamber for PTC [CRY], clean booth on access [FCL],	module tubes [VAC], baffles for gas molecules [VAC], gate vulves [VAC], feedthrough [VAC], PTC head [CRY], valve unit support [CRY], 2nd cold stage [CRY], defrosters [CRY],
--	--	---

## 2.4 Suspension-system components

Type-A IP [VIS],  
Type-A filter1 [VIS],  
Type-B filter1 [VIS],  
piezo-motor (filter2, PF) [VIS],  
position sensors (PF, MB) [VIS],  
PF local control servos [VIS],  
PF [VIS],  
Type-A RM [VIS],  
heat link A [CRY],  
RM wire [CRY],  
stacks for Type-B (iLCGT) [VIS],  
300K mirror wire [VIS],

Type-B IP [VIS],  
Type-A filter2 [VIS],  
MGAS [VIS],  
mini-GAS on PF [VIS],  
coil-magnet actuators (PF, MB) [VIS],  
MB local control servos [VIS],  
MB [VIS],  
Type-B RM [VIS],  
heat link B [CRY],  
TM fiber (sapphire) [CRY],  
300K IM wire [VIS],

Type-A filter0 [VIS],  
Type-B filter0 [VIS],  
horizontal-LVDT [VIS],  
motor slider on PF [VIS],  
ESD actuators [VIS],  
IM local control servos [VIS],  
IM [VIS],  
Type-C RM [VIS],  
IM wire [CRY],  
stacks for Type-C [VIS],  
300K RM wire [VIS],

## 2.5 Laser and input optics components

40W SFA [LAS],  
power supply [LAS],  
EOM for PMC [AEL],  
piezo actuators for PMC [AEL],  
AOM for RC [AEL],  
piezo actuators for RC [AEL],  
AOM for gr1 [AEL],  
PMC for gr1 [IOO],  
EOM for PMC for gr2 [AEL],  
FIs for green (2) [AOS],  
RF oscillator for gr1 PMC [AEL],  
RF oscillator for gr2 PDH [AEL],  
PD for gr1 PDH [AEL],  
dielectric mirrors [MIR],  
f2 PM EOM [AEL],  
PD for MZ refl [AEL],  
PD for MC refl [AEL],  
lenses for MC WFS [AOS],  
oplev for MC [AOS],  
variable attenuator [IOO],  
MMT mirrors [MIR],

Laser modules [LAS],  
FIs (4) [AOS],  
RF oscillator for PMC EOM [AEL],  
RC mirrors [IOO],  
PD for RC control [AEL],  
green laser 1 (X arm) [LAS],  
AOM for gr2 [AEL],  
PMC for gr2 [IOO],  
EOM for gr1 PDH [AEL],  
MMT for gr1 [AOS],  
RF oscillator for gr2 PMC [AEL],  
PD for gr1 PMC [AEL],  
PD for gr2 PDH [AEL],  
MZ mirrors [MIR],  
f1 AM EOMs [AEL],  
PD for MZ trans [AEL],  
PD for MC trans [AEL],  
MC servo [IOO],  
digital system for MC [DGS],  
PD for ISS [AEL],

water chiller [LAS],  
PMC mirrors [IOO],  
PD for PMC control [AEL],  
EOPM for RC [AEL],  
RC servo [IOO],  
green laser 2 (Y arm) [LAS],  
phase-lock system for green [IOO],  
EOM for PMC for gr1 [AEL],  
EOM for gr2 PDH [AEL],  
MMT for gr2 [AOS],  
RF oscillator for gr1 PDH [AEL],  
PD for gr2 PMC [AEL],  
piezo for green PMCs [AEL],  
f1 PM EOM [AEL],  
Pockels cell actuator for MZ [AEL],  
MC mirrors [MIR],  
QPDs for MC [AEL],  
CCDs for MC [AEL],  
beam shutter [AOS],  
ISS servos [IOO],

## 2.6 Main interferometer and core optics

ITM (silica) [MIR],  
ETM (sapphire) [MIR],  
PR2 [MIR],  
SR2 [MIR],  
steering mirrors [AOS],  
PD for REFL (high/low) [AEL],  
PD for POX [AEL],  
PD for Y-trans [AEL],  
QPDs for AS (high/low) [AEL],  
lenses for AS WFS [MIF],  
CCDs for trans (X,Y) [MIF],  
CARM demodulator [AEL],  
MICH demodulator [AEL],  
digital system for MIF [DGS],  
network analyzer [MIF],  
TCS (if necessary) [AOS],

ETM (silica) [MIR],  
BS [MIR],  
PR3 [MIR],  
SR3 [MIR],  
pico-motors for steering mirrors [AOS],  
PD for POP (high/low) [AEL],  
PD for POY [AEL],  
QPDs for REFL (high/low) [AEL],  
lenses for REFL WFS [MIF],  
olev for core optics [AOS],  
CCDs for REFL [MIF],  
DARM demodulator (RF) [AEL],  
SRCL demodulator [AEL],  
in-vacuum mirror cleaning tools [AOS],  
optical spectrum analyzer [MIF],  
beam reducing telescope [AOS],

ITM (sapphire) [MIR],  
PRM [MIR],  
SRM [MIR],  
ASp pickoff mirror [MIR],  
beam dampers [AOS],  
PD for ASp (high/low) [AEL],  
PD for X-trans [AEL],  
QPDs for POP (high/low) [AEL],  
lenses for POP WFS [MIF],  
holes on baffles [AOS],  
attenuation mirror for REFL [MIF],  
PRCL demodulator [AEL],  
CARM servo [MIF],  
oscilloscopes [MIF],  
acoustic isolation boxes [FCL],

## 2.7 Output optics components

OMC mirrors [MIR],  
piezo actuators for OMC [AEL],  
PD for OMC trans [AEL],

OMC breadboard [IOO],  
blackholes for OMC refl stray [AOS],  
output Faraday Isolator [AOS],

OMC breadboard actuators [AEL],  
QPD for OMC refl [AEL],

## 2.8 Control system components

main system PC [DGS],  
whitening/dewhitening filters [DGS],  
monitor software [DGS],  
control scripts [MIF],

ADC/DAC [DGS],  
real-time OS [DGS],  
data storage [DGS],

AA/AI filters [DGS],  
control software [DGS],  
timing system [DGS],

## 3 Interface parameters

### 3.1 AEL

The components that the AEL subsystem is in charge are as follows:

EOM for PMC, RF oscillator for PMC EOM, PD for PMC control, piezo actuators for PMC, EOPM for RC, AOM for RC, PD for RC control, piezo actuators for RC, AOM for gr1, AOM for gr2, EOM for PMC for gr1, EOM for PMC for gr2, EOM for gr1 PDH, EOM for gr2 PDH, RF oscillator for gr1 PMC, RF oscillator for gr2 PMC, RF oscillator for gr1 PDH, RF oscillator for gr2 PDH, PD for gr1 PMC, PD for gr2 PMC, PD for gr1 PDH, PD for gr2 PDH, piezo for green PMCs, f1 PM EOM, f2 PM EOM, f1 AM EOMs, Pockels cell actuator for MZ, PD for MZ refl, PD for MZ trans, PD for MC refl, PD for MC trans, QPDs for MC, CCDs for MC, PD for ISS, PD for REFL (high/low), PD for POP (high/low), PD for ASp (high/low), PD for POX, PD for POY, PD for X-trans, PD for Y-trans, QPDs for REFL (high/low), QPDs for POP (high/low), QPDs for AS (high/low), CARM demodulator, DARM demodulator (RF), PRCL demodulator, MICH demodulator, SRCL demodulator, OMC breadboard actuators, piezo actuators for OMC, QPD for OMC refl, PD for OMC trans,

and the related interface parameters are listed in Table 1.

### **3.2 AOS**

The components that the AOS subsystem is in charge are as follows:

FIs (4), FIs for green (2), MMT for gr1, MMT for gr2, lenses for MC WFS, oplev for MC, beam shutter, steering mirrors, pico-motors for steering mirrors, beam dampers, oplev for core optics, holes on baffles, in-vacuum mirror cleaning tools, TCS (if necessary), beam reducing telescope, blackholes for OMC refl stray, output Faraday Isolator,

and the related interface parameters are listed in Table 2.

### **3.3 CRY**

The components that the CRY subsystem is in charge are as follows:

radiation shields (8K, 80K), radiation shield supports, PTC head, compressor, valve unit, valve unit support, vibration reduction system, 1st cold stage, 2nd cold stage, heat conductors, vacuum chamber for PTC, defrosters, heat link A, heat link B, IM wire, RM wire, TM fiber (sapphire),

and the related interface parameters are listed in Table 3.

### **3.4 DGS**

The components that the DGS subsystem is in charge are as follows:

digital system for MC, digital system for MIF, main system PC, ADC/DAC, AA/AI filters, whitening/dewhitening filters, real-time OS, control software, monitor software, data storage, timing system,

and the related interface parameters are listed in Table 5.

### **3.5 FCL**

The components that the FCL subsystem is in charge are as follows:

buildings, car parking, power supply system, clean assy rooms, air conditioners, optical fibers, cranes, vacuum access, clean booth on access, acoustic isolation boxes,

and the related interface parameters are listed in Table 6.

### **3.6 GIF**

The components that the GIF subsystem is in charge are as follows:

thermometers, seismometers, particle meters, microphones, hygrometers, baseline interferometers, barometers, accelerometers,

and the related interface parameters are listed in Table 7.

### **3.7 IOO**

The components that the IOO subsystem is in charge are as follows:

PMC mirrors, RC mirrors, RC servo, phase-lock system for green, PMC for gr1, PMC for gr2, MC servo, variable

attenuator, ISS servos, OMC breadboard,

and the related interface parameters are listed in Table 8.

### **3.8 LAS**

The components that the LAS subsystem is in charge are as follows:

40W SFA, Laser modules, water chiller, power supply, green laser 1 (X arm), green laser 2 (Y arm),

and the related interface parameters are listed in Table 9.

### **3.9 MIF**

The components that the MIF subsystem is in charge are as follows:

lenses for REFL WFS, lenses for POP WFS, lenses for AS WFS, CCDs for trans (X,Y), CCDs for REFL, attenuation mirror for REFL, CARM servo, oscilloscopes, network analyzer, optical spectrum analyzer, control scripts,

and the related interface parameters are listed in Table 10.

### **3.10 MIR**

The components that the MIR subsystem is in charge are as follows:

dielectric mirrors, MZ mirrors, MC mirrors, MMT mirrors, ITM (silica), ETM (silica), ITM (sapphire), ETM (sapphire), BS, PRM, PR2, PR3, SRM, SR2, SR3, ASp pickoff mirror, OMC mirrors,

and the related interface parameters are listed in Table 11.

### **3.11 TUN**

The components that the TUN subsystem is in charge are as follows:

3km tunnels, center room, two-story end rooms, Water drainage system, entrance tunnel,

and the related interface parameters are listed in Table 13.

### **3.12 VAC**

The components that the VAC subsystem is in charge are as follows:

chambers (A,B,C1,C2), beam tubes, module tubes, borehole tubes, bellows, baffles for gas molecules, baffles for radiation, viewports, gate vulves, vacuum gauges, vacuum pumps (turbo, ion), feedthrough,

and the related interface parameters are listed in Table 14.

### **3.13 VIS**

The components that the VIS subsystem is in charge are as follows:

Type-A IP, Type-B IP, Type-A filter0, Type-A filter1, Type-A filter2, Type-B filter0, Type-B filter1, MGAS, horizontal-LVDT, piezo-motor (filter2, PF), mini-GAS on PF, motor slider on PF, position sensors (PF, MB), coil-magnet actuators (PF, MB), ESD actuators, PF local control servos, MB local control servos, IM local control servos, PF, MB, IM, Type-A RM, Type-B RM, Type-C RM, stacks for Type-C, stacks for Type-B (iLCGT), 300K IM wire, 300K RM wire, 300K mirror wire,

and the related interface parameters are listed in Table 15.

## 4 Optical layout

The Optical layout of bLCGT is shown in JGW-D1100685-v1 (dxf file).

## 5 Schedule

The Schedule of LCGT is shown here: <http://gwlcgt.icrr.u-tokyo.ac.jp:13013/PWA> (mpp file; password protected).

## 6 Glossary

AA : *anti-aliasing*

ADC : *analog-digital converter*

AI : *anti-imaging*

AOM : *acoustic-optic modulator*

AR : *anti-reflective coating*

AS : *anti-symmetric port*

BS : *beamsplitter*

CARM : *common-mode arm length change*

CMR(R) : *common-mode rejection (rate)*

DAC : *digital-analog converter*

DARM : *differential-mode arm length change*

EOM : *electro-optic modulator*

ESD : *electro-static drive*

ETM : *end test mass*

FI : *Faraday isolator*

FSS : *frequency stabilization system*

HOM : *higher order mode*

IM : *intermediate mass*

IP : *inverted pendulum*

ISS : *intensity stabilization system*

ITM : *input test mass*

LVDT : *linear variable differential transformer*

MB : *magnet block*

MC : *mode-cleaner*

MGAS : *monolithic geometrical anti-spring*

MICH : *differential length change of BS and ITMs*

MMT : *mode-matching telescope*

MZ : *Mach-Zehnder*

OMC : *output mode-cleaner*

PD : *photo-detector*

PDH : *Pound-Drever-Hall method*

PF : *platform*  
PMC : *pre-mode-cleaner*  
POM : *pick-off mirror*  
POP : *pick-off port in PRC*  
POX : *pick-off port from ITMx AR*  
POY : *pick-off port from ITMy AR*  
PRCL : *power-recycling cavity length change*  
PRM : *power-recycling mirror*  
PTC : *pulse tube cooler*  
QPD : *quadrant photo-detector*  
RC : *recycling cavity*  
REFL : *reflection port*  
RM : *recoil mass*  
RMS : *root mean square*  
RMTM : *recoil mass of test mass*  
RoC : *radius of curvature*  
SAS : *seismic attenuation system*  
SFA : *single frequency amplifier*  
SRCL : *signal-recycling cavity length change*  
SRM : *signal-recycling mirror*  
TCS : *thermal compensation system*  
TM : *test mass*  
WFS : *wave-front sensing*

## 7 Other constants

Other constants are listed in Table 16.

			TU	FA	VA	VI	MI	CR	IF	DG	EL	IO	LA	AO	GI	DA
drange_PD	TBD		PD dynamic range						IF	DG	EL	IO		AO		
drange_QPD	TBD		QPD dynamic range						IF	DG	EL	IO		AO		
aperture_rfpd_hi	3.00.E-03	m	RF PD aperture (high)						IF		EL					
aperture_rfpd_lo	3.00.E-03	m	RF PD aperture (low)						IF		EL					
aperture_dcpd_hi	3.00.E-03	m	DC PD aperture (high)						IF		EL					
aperture_dcpd_lo	3.00.E-03	m	DC PD aperture (low)						IF		EL					
input_rfpd_high	3.00.E-01	W	RF PD input power (h)						IF		EL					
input_rfpd_low	1.00.E-01	W	RF PD input power (l)						IF		EL					
input_dcpd_high	1.00.E-01	W	DC PD input power (h)						IF		EL					
input_dcpd_low	1.00.E-02	W	DC PD input power (l)						IF		EL					
RFHOMsuppress	TBD		RF HOM suppression a						IF		EL					
dcpowersupply	2.40.E+01	V	DC power supply						IF		EL					
dcvoltage	1.00.E-01	V	maximum DC voltage f						IF		EL			AO		
noise_PD	1.00.E-09	V/rtHz	electric noise on de						IF		EL			AO		
error_IQ	1.00.E-02		error of 90deg for I						IF	DG	EL					
loss_PD	5.00.E-02		1 – quantum efficien						IF		EL	IO		AO		
noise_QPD	1.00.E-09	V/rtHz	QPD noise						IF	DG	EL	IO		AO		
actuator_IM	TBD		actuator power on IM			VI			IF		EL					
actuate_range	TBD		actuation range (AC)		VI				IF		EL					
noise_actuator	TBD		actuator noise		VI				IF		EL					
actuator_ITM	TBD		actuator power on IT		VI				IF		EL			AO		
actuator_ETM	TBD		actuator power on ET		VI				IF		EL			AO		

Table 1: Interface parameters that AEL subsystem is in charge of.

				TU	FA	VA	VI	MI	CR	IF	DG	EL	IO	LA	AO	GI	DA
emissiv_baf_TM	TBD		emissivity of baffle					MI	CR						AO		
emissiv_baf_rs	TBD		emissivity of baffle					MI	CR						AO		
heat_viewport	1.00.E-02	W	heat from view ports		VA			CR	IF						AO		
FI_extinction	4.00.E+01	dB	extinction ratio of						IF				IO		AO		
outFI_extinction	4.00.E+01	dB	extinction ratio of						IF				IO		AO		
loss_outFI	2.00.E-02		optical loss of outp						IF				IO		AO		
centering	1.00.E-04	m	Beam centering error					MI		IF			IO		AO		
num_viewport	1.00.E+00		number of view ports		VA			CR	IF						AO		

Table 2: Interface parameters that AOS subsystem is in charge of.

			TU	FA	VA	VI	MI	CR	IF	DG	EL	IO	LA	AO	GI	DA
emissivity_TM	8.00.E-02	emmisivity of surfac					MI	CR								
Tm_TM	2.00.E+01	K	temperature				MI	CR	IF							
specificheat_TM	6.90.E-01	J/K/kg	specific heat of TM				VI	MI	CR							
kappa_TM	1.57.E+04	W/m/K	thermal conducutivit				VI	MI	CR							
diameter_cryo8K	5.00.E-01	m	radiation shield dia		VA			CR								
emissivity_vacuu	3.00.E-02		duct emissivity		VA			CR								
heat_fromBS	1.00.E-01	W	radiation from BS ch		VA			CR	IF							
heat_fromArm	1.00.E-01	W	radiation from arm c		VA			CR	IF							
heat_cryoshield	1.00.E-01	W	heat from radiation		VA			CR	IF							
diameter_apertur	2.50.E-01	m	radiation shield ape		VA			CR	IF						AO	
heat_scatter_tos	4.00.E+00	W	max heat from scatte		VA		MI	CR	IF						AO	
seis_cryostat	TBD		vibration at cryosta	TU	FA	VA		CR	IF							
diameter_tophole	1.50.E-01	m	top hole diameter (t		VA	VI		CR	IF							
heat_fromtop	1.00.E-02	W	radiation from upper		VA	VI		CR	IF							
Tm_cryo8K	8.00.E+00	K	inner shield temepra		VA	VI		CR	IF							
Tm_cryo80K	8.00.E+01	K	duct shield temperat		VA	VI		CR	IF							
kappa heatlink	4.00.E+03	W/m/K	heat link thermal co		VI			CR								
num_HL1	7.00.E+00		number of HL1 (Sh-PF)			VI		CR								
RRR_HL1	4.00.E+03		RRR of HL1 (Sh-PF)			VI		CR								
RoU_HL1	5.00.E-01	m	HL1 radius of U			VI		CR								
Isus_HL1	7.50.E-01	m	HL1 length			VI		CR								
ksus_HL1	TBD		HL1 spring constant		VI			CR								
diameter_HL1	1.00.E-03	m	HL1 diameter			VI		CR								
loss_HL1	5.00.E-05		HL1 loss			VI		CR								
num_HL2	5.00.E+00		number of HL2 (PF-IM			VI		CR								
RRR_HL2	4.00.E+03		RRR of HL2 (Sh-PF)			VI		CR								
RoU_HL2	4.00.E-01		HL2 radius of U			VI		CR								
Isus_HL2	6.28.E-01	m	HL2 length			VI		CR								
ksus_HL2	TBD		HL2 spring constant			VI		CR								
diameter_HL2	3.00.E-03	m	HL2 diameter			VI		CR								
loss_HL2	5.00.E-05		HL2 loss			VI		CR								
num_HL3	4.00.E+00		number of HL3 (IM-RM			VI		CR								
RRR_HL3	4.00.E+03		RRR of HL3 (Sh-PF)			VI		CR								
RoU_HL3	3.00.E-01		HL3 radius of U			VI		CR								
Isus_HL3	4.71.E-01		HL3 length			VI		CR								
ksus_HL3	TBD		HL3 spring constant			VI		CR								
diameter_HL3	1.60.E-03		HL3 diameter			VI		CR								
loss_HL3	5.00.E-05		HL3 loss			VI		CR								
m_IM	6.00.E+01	kg	mass of IM			VI		CR								
RRR_IM	2.00.E+01		RRR of IM			VI		CR								
width_IM	3.10.E-01	m	IM width			VI		CR								
depth_IM	2.00.E-01	m	IM depth			VI		CR								
thickness_IM	1.10.E-01	m	IM thickness			VI		CR								
Tm_IM	TBD	K	temperature of IM			VI		CR								
emissivity_IM	2.00.E-02		emmisivity of surfac			VI		CR								
Cs_IM	TBD		specific heat of IM			VI		CR								
kappa_IM	TBD		thermal conducutivit			VI		CR								
num_IMwires	4.00.E+00		number of wires (IM)			VI		CR								
E_IMwire	1.61.E+11	Pa	wire Young's modulus			VI		CR								
tensile_IM	5.00.E+09	Pa	wire tensile strengt			VI		CR								
loss_Imwire	1.00.E-04		loss			VI		CR								
kappa_Imwire	TBD		thermal conductivity			VI		CR								
Isus_IM	4.00.E-01	m	length			VI		CR								
dsus_IM	7.20.E-04	m	diameter			VI		CR								
rho_Imwire	1.93.E+04	kg/m^3	density			VI		CR								
Tm_Imwire	1.00.E+01	K	temperature of IM wi			VI		CR								
Tm_RM	1.50.E+01	K	temperature of RMTM			VI		CR								
emissivity_RM	2.00.E-02		emmisivity of surfac			VI		CR								
Cs_RM	TBD		specific heat of RMT			VI		CR								
kappa_RM	TBD		thermal conducutivit			VI		CR								
kappa_RMwire	TBD		thermal conductivity			VI		CR								
Isus_RM	3.00.E-01	m	length (RM wire)			VI		CR								
dsus_RM	4.00.E-04	m	diameter (RM wire)			VI		CR								
num_RMwire	4.00.E+00		number of fibers (RM			VI		CR								
E_RMwire	1.30.E+11	Pa	Young's modulus (RM			VI		CR								

Table 3: Interface parameters (1) that CRY subsystem is in charge of.

<code>rho_RMwire</code>	8.36.E+03	$\text{kg/m}^3$	density (RM wire)			<b>VI</b>	<b>CR</b>					
<code>Tm_RMwire</code>	1.60.E+01	K	effective temperatur			<b>VI</b>	<b>CR</b>					
<code>loss_yaw_IM</code>	TBD		yaw-mode loss (IM)			<b>VI</b>	<b>CR IF</b>					
<code>loss_pitch_IM</code>	TBD		pitch-mode loss (IM)			<b>VI</b>	<b>CR IF</b>					
<code>f_yaw_IM</code>	TBD		yaw-mode resonant fr			<b>VI</b>	<b>CR IF</b>				<b>AO</b>	
<code>f_pitch_IM</code>	TBD		pitch-mode resonant			<b>VI</b>	<b>CR IF</b>				<b>AO</b>	
<code>inertia_yaw_IM</code>	TBD		yaw-mode moment of i			<b>VI</b>	<b>CR IF</b>				<b>AO</b>	
<code>inertia_pitch_IM</code>	TBD		pitch-mode moment of			<b>VI</b>	<b>CR IF</b>				<b>AO</b>	

Table 4: Interface parameters (2) that CRY subsystem is in charge of.

				TU	FA	VA	VI	MU	CR	IF	DG	EL	IO	LA	AO	GI	DA
noise_adc	2.00.E-06	V/rtHz	ADC noise				VI			IF	DG	EL	IO	LA			
noise_dac	1.50.E-06	V/rtHz	DAC noise				VI			IF	DG	EL	IO	LA			
max_adc	2.00.E+01	V	ADC maximum input vo				VI			IF	DG	EL	IO	LA			
max_dac	1.00.E+01	V	DAC maximum output v				VI			IF	DG	EL	IO	LA			
sampling	1.64.E+04	Hz	sampling frequency				VI			IF	DG	EL	IO	LA			DA
loopdelay	1.00.E-04	sec	loop time delay (>20				VI			IF	DG	EL	IO	LA			DA
bandwidth	7.40.E+03	Hz	observation bandwidt							IF	DG						DA

Table 5: Interface parameters that DGS subsystem is in charge of.

				TU	FA	VA	VI	MI	CR	IF	DG	EL	IO	LA	AO	GI	DA
Tm_room	2.90.E+02	K	room temperature		FA				CR	IF						GI	
clean_manu	0		cleanliness in manuf		FA			MI									
clean_lab	0		cleanliness in lab		FA			MI									
clean_buil	0		cleanliness in build		FA			MI									

Table 6: Interface parameters that FCL subsystem is in charge of.

			<b>TU</b>	<b>FA</b>	<b>VA</b>	<b>VI</b>	<b>MU</b>	<b>CR</b>	<b>IF</b>	<b>DG</b>	<b>EL</b>	<b>IO</b>	<b>LA</b>	<b>AO</b>	<b>GI</b>	<b>DA</b>
barometer	TBD	barometer resolution		FA	VA	VI			IF	DG					GI	DA
hygrometer	TBD	hygrometer resolutio		FA	VA	VI			IF	DG					GI	DA
thermometer	TBD	thermometer resoluti		FA		VI			IF	DG					GI	DA
microphone	TBD	microphone resolutio		FA		VI			IF	DG					GI	DA
particlemeter	TBD	particle meter resol	<b>TU</b>	FA	VA	VI			IF	DG					GI	DA
accelerometer	TBD	accelerometer resolu				VI			IF	DG					GI	DA
seismometer	TBD	seismometer resoluti	<b>TU</b>	FA		VI			IF	DG					GI	DA

Table 7: Interface parameters that GIF subsystem is in charge of.

			TU	FA	VA	VI	MU	CR	IF	DG	EL	IO	LA	AO	GI	DA
L_PMC	4.88.E-01	m	PMC length						IF		IO	IO				
noise_oscillator	-1.60.E+01	dBc	RF oscillator phase						IF	EL	IO					
L_RC	1.50.E-01	m	Ref Cav length								IO		AO			
finesse_RC	1.00.E+04		Ref Cav finesse								IO		AO			
trans_MC	0.8		MC transmittance								IO	LA				
noise_FSSPD	1.00.E-09	V//rtHz	FSS PD noise level						IF	EL	IO		AO			
power_FSS	1.00.E-01	W	pick-off power for F						IF		IO		AO			
angle_MCend	5.42.E-01	deg	angle of incidence o						IF		IO		AO			
w_MCend	4.38.E-03	m	beam radius on MC-en						IF		IO		AO			
w_MCin	2.53.E-03	m	beam radius on MC-in						IF		IO		AO			
w_MCout	2.53.E-03	m	beam radius on MC-ou						IF		IO		AO			
finesse_MC	5.00.E+02		MC finesse						IF		IO		AO			
beamjitter_MC	TBD		MC output beam jitte						IF		IO		AO			
L_MCout_MM1	5.80.E+00	m	distance of MC-out a						IF		IO		AO			
L_MM1_MM2	5.60.E+00	m	distance of MM1 and						IF		IO		AO			
L_MM2_PRM	5.80.E+00	m	distance of MM2 and						IF		IO		AO			
L_OMC	8.00.E-01	m	OMC length						IF		IO		AO			
dither_length_OM	TBD		dither freq for OMC						IF		IO		AO			
dither_angle_OMC	TBD		dither freq for OMC						IF		IO		AO			
num_mirror_OMC	4.00.E+00		number of mirrors (O)					MI	IF		IO		AO			
loss_OMC	5.00.E-02		OMC optical loss					MI	IF		IO		AO			
finesse_OMC	5.00.E+02		OMC finesse					MI	IF		IO		AO			
num_mirror_PMC	4.00.E+00		number of mirrors (P)					MI			IO					
finesse_PMC	1.55.E+02		PMC finesse					MI			IO					
diameter_MM1	1.00.E-01	m	MMT mirror diameter					MI			IO		AO			
thickness_MM1	3.00.E-02	m	MMT mirror thickness					MI			IO		AO			
RoC_MM1	2.06.E+01	m	MMT1 RoC					MI			IO		AO			
RoC_MM2	2.61.E+01	m	MMT2 RoC					MI			IO		AO			
R_MCend	1.00.E+00		MC-end reflectivity					MI	IF		IO		AO			
R_MCin	9.94.E-01		MC-in reflectivity					MI	IF		IO		AO			
R_MCout	9.94.E-01		MC-out reflectivity					MI	IF		IO		AO			
L_MC	5.33.E+01	m	MC length (roundtrip		VA				IF		IO		AO			
mass_OMCplatform	TBD		mass of OMC platform			VI					IO					
reso_OMCsusp	TBD		resonant freq of OMC			VI					IO					

Table 8: Interface parameters that IOO subsystem is in charge of.

				TU	FA	VA	VI	MI	CR	IF	DG	EL	IO	LA	AO	GI	DA
wavelength	1.06.E-06	m	wavelength											LA			
FN	1.00.E+02	Hz/rtHz	free-run FN (at 100H)											LA			
IN	1.00.E-04	W/W/rtH	free-run IN											LA			
laser_linewidth	TBD		linewidth											LA			
chiller	1.50.E+01	deg	chiller temperature											LA			
laser_temperatur	TBD		Laser temperature											LA			
laserpower	1.80.E+02	W	laser power							IF			IO	LA			
laserpower_green	1.00.E-01	W	Green Laser power							IF			IO	LA	AO		
freq_gap_green	1.00.E+08	Hz	Green laser's freque							IF			IO	LA	AO		

Table 9: Interface parameters that LAS subsystem is in charge of.

			TU	FA	VA	VI	MU	CR	IF	DG	EL	IO	LA	AO	GI	DA
contrastdefect	5.00.E-03		contrast defect (ali						IF					AO		
guoy_PRC	2.00.E+01	deg	Gouy phase shift in						IF					AO		
guoy_SRC	2.00.E+01	deg	Gouy phase shift in						IF					AO		
offset_arm	2.00.E-12	m	differential offset						IF			IO				
detune	3.50.E+00	deg	detune phase						IF			IO				
f1	1.69.E+07	Hz	f1 sideband frequenc						IF			IO		AO		
mod_f1	2.00.E-01		f1 sideband modulati						IF			IO		AO		
f2	4.50.E+07	Hz	f2 sideband frequenc						IF			IO		AO		
mod_f2	2.00.E-01		f2 sideband modulati						IF			IO		AO		
f3	3.94.E+07	Hz	f3 sideband freq (if						IF			IO		AO		
mod_f3	0.00.E+00		f3 sideband modulati						IF			IO		AO		
RIN_AF	TBD		AF RIN						IF			IO	LA	AO		
RIN_RF	1.00.E-09	W/W/rtH	RF RIN (>15MHz)						IF			IO	LA	AO		
num_coat_ETM	1.80.E+01		number of layers on					MI	IF							
num_coat_ITM	9.00.E+00		number of layers on					MI	IF							
m_ETM	2.28.E+01	kg	ETM mass					MI	IF							
m_ITM	2.28.E+01	kg	ITM mass					MI	IF							
finesse_green	1.90.E+01		Green arm finesse (I					MI	IF					AO		
R_BS_green	1.00.E-02		BS reflectivity for					MI	IF					AO		
R_PR2_green	1.00.E-02		PR2 reflectivity for					MI	IF					AO		
R_PR3_green	1.00.E-02		PR3 reflectivity for					MI	IF					AO		
R_SR2_green	1.00.E-02		SR2 reflectivity for					MI	IF					AO		
R_SR3_green	1.00.E-02		SR3 reflectivity for					MI	IF					AO		
R_PRM	9.00.E-01		PRM reflectivity					MI	IF					AO		
loss_PRM	1.00.E-04		PRM optical loss					MI	IF					AO		
loss_PR2	1.00.E-04		PR2 optical loss					MI	IF					AO		
loss_PR3	1.00.E-04		PR3 optical loss					MI	IF					AO		
RoC_PRM	3.70.E+02	m	RoC of PRM					MI	IF					AO		
RoC_PR2	4.17.E+00	m	RoC of PR2					MI	IF					AO		
RoC_PR3	3.23.E+01	m	RoC of PR3					MI	IF					AO		
R_SRM	9.00.E-01		SRM reflectivity					MI	IF					AO		
loss_SRM	1.00.E-04		SRM optical loss					MI	IF					AO		
loss_SR2	1.00.E+04		SR2 optical loss					MI	IF					AO		
loss_SR3	1.00.E+04		SR3 optical loss					MI	IF					AO		
RoC_SRM	3.70.E+02	m	RoC of SRM					MI	IF					AO		
RoC_SR2	4.17.E+00	m	RoC of SR2					MI	IF					AO		
RoC_SR3	3.23.E+01	m	RoC of SR3					MI	IF					AO		
R_ETM	1.00.E+00		ETM reflectivity					MI	IF					AO		
R_ITM	9.96.E-01		ITM reflectivity					MI	IF					AO		
R_ASp	0.00.E+00		AS POM reflectivity					MI	IF				IO	AO		
w_ETM	4.53.E-02	m	beam radius on ETM					MI	IF				IO	AO		
w_ITM	3.43.E-02	m	beam radius on ITM					MI	IF				IO	AO		
wedge_PRM	3.00.E-01	deg	wedge angle of PRM (			VA	MI	IF				IO		AO		
wedge_SRM	3.00.E-01	deg	wedge angle of SRM			VA	MI	IF				IO		AO		
L_arm	3.00.E+03	m	arm length			VA			IF							
L_PRM_PR2	1.4761.E+1	m	PRM-PR2 distance			VA			IF					AO		
L_PR2_PR3	1.2067.E+1	m	PR2-PR3 distance			VA			IF					AO		
L_PR3_BS	1.4764.E+1	m	PR3-BS distance			VA			IF					AO		
L_SRM_SR2	1.4764.E+1	m	SRM-SR2 distance			VA			IF					AO		
L_SR2_SR3	1.2067.E+1	m	SR2-SR3 distance			VA			IF					AO		
L_SR3_BS	1.4764.E+1	m	SR3-BS distance			VA			IF					AO		
foldangle_PRC	6.293.E-01	deg	PRC folding angle			VA			IF					AO		
foldangle_SRC	6.293.E-01	deg	SRC folding angle			VA			IF					AO		
L_BS_ITM	2.50285.E	m	BS-ITM average dista			VA			IF					AO		
L_asym	3.33.E+00	m	asymmetry length			VA			IF					AO		
rms	1.00.E-14	m	rms fluctuation of D			VI			IF							
UGF_CARM	1.00.E+04	Hz	CARM UGF			VI			IF			EL				
UGF_DARM	2.00.E+02	Hz	DARM UGF			VI			IF			EL				
UGF_PRCL	2.00.E+01	Hz	PRCL UGF			VI			IF			EL				
UGF_MICH	2.00.E+01	Hz	MICH UGF			VI			IF			EL				
UGF_SRCL	2.00.E+01	Hz	SRCL UGF			VI			IF			EL				
FF_PRCL	1.00.E+02		PRCL FF gain			VI			IF			EL				
FF_MICH	1.00.E+02		MICH FF gain			VI			IF			EL				
FF_SRCL	1.00.E+02		SRCL FF gain			VI			IF			EL				

Table 10: Interface parameters that MIF subsystem is in charge of.

			TU	FA	VA	VI	M1	CR	IF	DG	EL	IO	LA	AO	GI	DA
rho_ETM	4.00.E+03	kg/m^3	mirror bulk density				M1									
rho_ITM	4.00.E+03	kg/m^3	mirror bulk density				M1									
E_ETM	4.00.E+11	Pa	Young's modulus of E				M1									
E_ITM	4.00.E+11	Pa	Young's modulus of I				M1									
sigma_ETM	2.90.E-01		mirror bulk Poisson				M1									
sigma_ITM	2.90.E-01		mirror bulk Poisson				M1									
alpha_ETM	5E-09	1/K	mirror thermal expan				M1	CR								
alpha_ITM	5E-09	1/K	mirror thermal expan				M1	CR								
Cs_ETM	6.90.E-01	J/K/kg	mirror specific heat				M1	CR								
Cs_ITM	6.90.E-01	J/K/kg	mirror specific heat				M1	CR								
kappa_ETM	1.57.E+04	W/m/K	mirror thermal condu				M1	CR								
kappa_ITM	1.57.E+04	W/m/K	mirror thermal condu				M1	CR								
E_coat_silica	7.20.E+10	Pa	silica coating Young				M1	CR								
E_coat_tantala	1.40.E+11	Pa	tantala coating Youn				M1	CR								
sigma_coat_silic	1.70.E-01		silica coating Poiss				M1	CR								
sigma_coat_tanta	2.30.E-01		tantala coating Pois				M1	CR								
Cv_coat_silica	1.64.E+06	J/K/m^3	silica coating speci				M1	CR								
Cv_coat_tantala	2.10.E+06	J/K/m^3	tantala coating spec				M1	CR								
alpha_coat_silic	5.10.E-07	1/K	silica coating therm				M1	CR								
alpha_coat_tanta	3.60.E-06	1/K	tantala coating ther				M1	CR								
alpha_coat_silic	1.38.E+00	W/m/K	silica coating therm				M1	CR								
alpha_coat_tanta	3.30.E+01	W/m/K	tantala coating ther				M1	CR								
diamter_TM	2.20.E-01	m	TM diameter				M1	CR	IF						AO	
thickness_TM	1.50.E-01	m	TM thickness				M1	CR	IF						AO	
abso_AR	1.00.E-06		AR surface absorptio				M1	CR	IF						AO	
R_BS	5.00.E-01		BS reflectivity				M1		IF							
loss_BS_HR	5.00.E-05		BS HR surface optica				M1		IF							
RoC_BS	5.00.E+05	m	RoC of BS				M1		IF							
abso_BS	1.50.E-04	1/m	BS substrate absorpt				M1		IF							
radisu_BS	1.90.E-01	m	BS radius				M1		IF						AO	
thickness_BS	1.20.E-01	m	BS thickness				M1		IF						AO	
loss_BS_AR	5.00.E-05		BS AR surface reflec				M1		IF						AO	
diameter_PRM	2.50.E-01	m	PRM diamter				M1		IF						AO	
thickness_PRM	1.00.E-01	m	PRM thickness				M1		IF						AO	
diameter_PR2	2.50.E-01	m	PR2 diamter				M1		IF						AO	
thickness_PR2	1.00.E-01	m	PR2 thickness				M1		IF						AO	
diameter_PR3	2.50.E-01	m	PR3 diameter				M1		IF						AO	
thickness_PR3	1.00.E-01	m	PR3 thickness				M1		IF						AO	
diameter_SRM	2.50.E-01	m	SRM diamter				M1		IF						AO	
thickness_SRM	1.00.E-01	m	SRM thickness				M1		IF						AO	
diameter_SR2	2.50.E-01	m	SR2 diamter				M1		IF						AO	
thickness_SR2	1.00.E-01	m	SR2 thickness				M1		IF						AO	
diameter_SR3	2.50.E-01	m	SR3 diameter				M1		IF						AO	
thickness_SR3	1.00.E-01	m	SR3 thickness				M1		IF						AO	
surfacerms_center	3.00.E-10	m	central region surfa				M1		IF						AO	
surfacerms_outer	1.00.E-09	m	outer region surface				M1		IF						AO	
surfacecenter	1.20.E-01	m	border of central re				M1		IF						AO	
flatness_AR_TM	TBD		AR side surface flat				M1		IF						AO	
RoC_TM_fromAR	TBD		ROC seen from AR sid				M1		IF						AO	
birefringence	TBD		birefringence				M1		IF						AO	
loss_ETM	4.50.E-05		ETM optical loss				M1		IF						AO	
loss_ITM	4.50.E-05		ITM optical loss				M1		IF						AO	
loss_imbalance	1.50.E-05		optical loss imbalan				M1		IF						AO	
finesse_imbalanc	5.00.E-03		finesse imbalance ra				M1		IF						AO	
RoCerror_ETM	1.00.E-02		RoC error of ETM				M1		IF						AO	
RoCerror_ITM	1.00.E-02		RoC error of ITM				M1		IF						AO	
RoC_ETM	7.00.E+03	m	RoC of ETM				M1		IF						AO	
RoC_ITM	5.00.E+05	m	RoC of ITM				M1		IF						AO	
RoCerror_diff	5.00.E-03		RoC imbalance in two				M1		IF						AO	
BRDF	1.40.E-05		BRDF				M1	CR	IF						AO	
mloss_ETM	1.00.E-08		mirror mechanical lo				M1	CR	IF							
mloss_ITM	1.00.E-08		mirror mechanical lo				M1	CR	IF							
mloss_coat_silic	3.00.E-04		silica coating loss				M1	CR	IF							
mloss_coat_tanta	5.00.E-04		tantala coating loss				M1	CR	IF							
loss_sleeks	TBD		scratches and sleeks				M1	CR	IF						AO	

Table 11: Interface parameters (1) that MIR subsystem is in charge of.

loss_points	1.00.E-05	point defects loss			<b>M1</b>	<b>CR</b>	<b>IF</b>			<b>AO</b>	
loss_ITMsubstrat	5.00.E-03	1/m	ITM substrate optica		<b>M1</b>	<b>CR</b>	<b>IF</b>			<b>AO</b>	
abs_coat	1.00.E-06	absorption at coatin			<b>M1</b>	<b>CR</b>	<b>IF</b>			<b>AO</b>	
loss_AR_ITM	1.00.E-04	ITM AR surface optic			<b>M1</b>	<b>CR</b>	<b>IF</b>			<b>AO</b>	
RoC_MCin	5.00.E+05	m	MC-in RoC		<b>M1</b>		<b>IF</b>		<b>IO</b>	<b>AO</b>	
RoC_MCout	5.00.E+05	m	MC-out RoC		<b>M1</b>		<b>IF</b>		<b>IO</b>	<b>AO</b>	
RoC_MCend	4.00.E+01	m	MC-end RoC		<b>M1</b>		<b>IF</b>		<b>IO</b>	<b>AO</b>	
diameter_MC	1.00.E-01	m	MC mirror diameter		<b>M1</b>		<b>IF</b>		<b>IO</b>	<b>AO</b>	
thickness_MC	3.00.E-02	m	MC mirror thickness		<b>M1</b>		<b>IF</b>		<b>IO</b>	<b>AO</b>	
wedge_BS	3.83.E-01	deg	AR wedge of BS		<b>VA</b>	<b>M1</b>	<b>IF</b>			<b>AO</b>	
wedge_ETM	3.00.E-01	deg	wedge angle of ETM		<b>VA</b>	<b>M1</b>	<b>IF</b>			<b>AO</b>	
wedge_ITM_sap	2.00.E-01	deg	wedge angle of ITM (		<b>VA</b>	<b>M1</b>	<b>IF</b>			<b>AO</b>	
wedge_ITM_sil	3.35.E-01	deg	wedge angle of ITM (		<b>VA</b>	<b>M1</b>	<b>IF</b>			<b>AO</b>	
ear_distance	2.46.E-01	m	distance of flat ear			<b>VI</b>	<b>M1</b>				

Table 12: Interface parameters (2) that MIR subsystem is in charge of.

				TU	FA	VA	VI	MU	CR	IF	DG	EL	IO	LA	AO	GI	DA
ip.tunnelsize	=4.00.E+01 %m	%tunnel width/height		TU													
ip.tilt_tunnel	=3.33.E-01 %	%tunnel tilt (diff at ETM)		TU													
ip.cmrr_seis	=TBD %	%CMRR (3km)		TU													
ip.cmrr_cutoff	=TBD %	%CMR cutoff frequency		TU													
ip.diameter_borehole	=1.20.E+01 %m	%diamter of borehole for		TU													
tunnelsize	4.00.E+00 m	tunnel width/height		TU	FA	VA			CR								
tilt_tunnel	3.33.E-03	tunnel tilt (diff at		TU	FA	VA			CR	IF			IO				
cmrr_seis	TBD	CMRR (3km)		TU	FA	VA	VI										
cmrr_cutoff	TBD	CMR cutoff frequency		TU	FA	VA	VI										
diameter_borehole	1.20.E+00 m	diamter of borehole		TU	FA	VA	VI										

Table 13: Interface parameters that TUN subsystem is in charge of.

			TU	FA	VA	VI	MI	CR	IF	DG	EL	IO	LA	AO	GI	DA
flatness_flange	1.00.E-04	m			VA											
thickness_flange	3.00.E-02	m			VA											
diameter_duct	8.00.E-01	m			VA			CR	IF					AO		
num_pump	3.00.E+01				FA	VA										
speed_ionpump	1.00.E+03	L/s			FA	VA										
speed_turbopump	2.00.E+03	L/s			FA	VA										
num_gv	2.00.E+00				FA	VA										
vacuum	2.00.E-07	Pa			FA	VA			IF							

Table 14: Interface parameters that VAC subsystem is in charge of.

				TU	FA	VA	VI	MU	CR	IF	DG	EL	IO	LA	AO	GI	DA	
k_GAS4	4.73.E+02	kg/s^2	spring constant of 4				VI											
loss_GAS4blade	1.00.E-02		loss of GAS filter b				VI											
m_joint	1.00.E-01	kg	mass of GAS filter j				VI											
lsus_GASPF	2.10.E+00	nm	wire length btw 4th				VI											
d_GAS4	3.11.E-03	m	wire diameter (4th G				VI											
n_GAS4	1.00.E+00		number of wires (4th				VI											
E_GAS4	1.86.E+11	Pa	wire young's modulus				VI											
tensile_GAS4	2.00.E+09	Pa	wire tensile strength				VI											
loss_GAS4wire	TBD		loss of wire (4th GA				VI											
lsus_GAS4	2.10.E+00	m	wire length btw 4th				VI											
m_payload	1.20.E+02	kg	total mass suspended				VI											
m_RM	3.00.E+01	kg	mass of RMTM				VI											
diameter_RMout	2.90.E-01	m	outer diameter				VI											
diameter_RMin	2.60.E-01	m	inner diameter				VI											
thickness_RM	2.60.E-01	m	thickness				VI											
loss_RMwire	5.00.E-06		loss (RM wire)				VI											
f_yaw_RM	TBD		yaw-mode resonance (				VI											
f_pitch_RM	TBD		pitch-mode resonance				VI											
loss_yaw_RM	TBD		yaw-mode loss (RM wi				VI											
loss_pitch_RM	TBD		pitch-mode loss (RM				VI											
inertia_yaw_RM	TBD		yaw-mode moment of i				VI											
inertia_pitch_RM	TBD		pitch-mode moment of				VI											
kappa_fiber_TM	7.00.E+03	W/m/K	thermal conductivity				VI											
lsus_TM	3.00.E-01	m	length (TM)				VI											
dsus_TM	1.60.E-03	m	diameter (TM)				VI											
num_TMfiber	4.00.E+00		number of fibers (TM				VI											
E_TMfiber	4.00.E+11	Pa	Young's modulus (TM				VI											
rho_TMfiber	4.00.E+03	kg/m^3	density (TM fiber)				VI											
Tm_TMfiber	1.60.E+01		effective temperatur				VI											
mloss_TMfiber	2.00.E-07		loss (TM fiber)				VI											
loss_yaw_TM	TBD		yaw-mode loss (TM)				VI											
loss_pitch_TM	TBD		pitch-mode loss (TM)				VI											
inertia_yaw_TM	TBD		yaw-mode moment of i				VI											
inertia_pitch_TM	TBD		pitch-mode moment of				VI											
f_yaw_TM	TBD		yaw-mode resonant fr				VI									AO		
f_pitch_TM	TBD		pitch-mode resonant				VI									AO		
dT_GAS4	TBD		T dependence of spri				VI											
dsus_GAS4	3.74.E-03	m	wire diameter (4th G				VI									DG	EL	
num_GAS4wire	1.00.E+00		number of wires (4th				VI									DG	EL	
adjust_range	1.00.E-02	m	adjustable distance				VI									IF	EL	
rms_SAS	1.00.E-07	m	RMS displacement				VI									IF	DG	EL
rms_SAS_velocity	1.00.E-07	m/s	RMS velocity				VI									IF	DG	EL
rms_pitch	TBD		RMS pitch				VI									IF	DG	EL
rms_yaw	TBD		RMS yaw				VI									IF	DG	EL
VHC	5.00.E-03		Vertical horizontal	TU	FA	VA	VI										GI	

Table 15: Interface parameters that VIS subsystem is in charge of.

Table 16: Other constants.